

## 13.9 REPORT

### 13.9.1 SERVICE DATA LIST

#### A. Use

**(1) Service Data list includes the following items:**

- SOFT SWITCH
- COMMUNICATION HISTORY & COUNTER
- ADJUST
- RX IN MEMORY
- ADMINISTRATOR PASSWORD
- MAIN RAM SIZE
- ROM ID

**(2) Error log history list includes the following items:**

- Index: Index number from 0 - 9999
- Error: Error code number
- Maker: NSF frame maker code
- Tell.: Remote side or TX side telephone number for that transaction

#### B. Procedure

1. Enter the [SERVICE MODE].
2. Select [REPORT] and press the Select key.
3. Select [SERVICE DATA LIST] and press the Select key.

(1) SERVICE DATA LIST (example)

SERVICE DATA LIST

NAME :
TEL :
DATE : NOV.26.2010 09:35

SOFT SWITCH
SW01-SW16
SW17-SW32
SW33-SW48
SW49-SW64

COMMUNICATION HISTORY & COUNTER
000000:ECM RX TIME
000000:63 RX TIME
000000:V.17 14.4K
000000:V.17 9.6K
000000:V.29 9.6K
000000:V.27 4.8K
000000:63 TX TIME
000000:V.17 14.4K
000000:V.17 9.6K
000000:V.29 9.6K
000000:V.27 4.8K
000000:V.34 RX TIME
000000:33.6K
000000:28.8K
000000:24.0K
000000:19.2K
000000:9.6K
000000:4.8K
000000:V.34 TX TIME
000000:33.6K
000000:28.8K
000000:24.0K
000000:19.2K
000000:9.6K
000000:4.8K
000000:JBIG TX TIME
000015:TOTAL COUNTER
000004:COPY PRINT
000011:REPORT PRINT

ADJUST
CIS MAIN ZOOM : 100
CIS SUB ZOOM : 100
CIS MAIN REGIST : 115
CIS SUB REGIST : 095
ADF MAIN REGIST : 095
ADF SUB ZOOM : 100
ADF SUB REGIST : 080
FUSER CONTROL : 0
TOP ADJ FRONT
PLAIN PAPER : 0
THICK1 : 0
THICK2 : -04
ENVELOPE : 0
LEFT ADJ FRONT
TRAY1 : 0
TRAY2 : 0
TRANSFER POWER
SIMPLEX PASS : 0
THICK1 : 0
THICK2 : 0
POSTCARD : 0
ENVELOPE : 0
LABEL : 0
GLOSSY1 : 0
GLOSSY2 : 0
DUPLEX PASS
PLAIN PAPER : 0
THICK1 : 0
THICK2 : 0
POSTCARD : 0
ENVELOPE : 0
LABEL : 0
GLOSSY1 : 0
GLOSSY2 : 0
IMAGE ADJ PARAM : 0
TEMPERATURE : 0
PLAIN PAPER : 0
THICK1 : 0
ENVELOPE : 0
THICK MODE : QUALITY MODE
FINE LINE ADJ : 0
IU YIELD SETTING : STANDARD
AIDC MODE : MODE2

RX IN MEMORY :
ADMIN. PASSWORD : 000000
MAIN RAM SIZE : 128Mb

ROM ID
MAIN : A2YF35G0010200
BOOT : A2YF98G0010000
ENGINE: A2YF-50F0-0100-00

A2YFF3C007DA

**(2) ERROR LOG HISTORY LIST (example)**

- The following table is the error log history. The table keeps the last 40 records only.

ERROR LOG HISTORY LIST			
Index	Error	Maker	Tele.
0001	:00A0	4230	88634733507
0002	:00A0	49EE	
0003	:0070	0000	
0004	:0070	0000	
0005	:0070	0000	
0006	:0070	0000	
0007	:0070	0000	
0008	:0070	0000	
0009	:0070	0000	123

NSF signal 3rd. and 4th byte      Keep 20 digits of TSI or CSI

4139F3E552DA

bizhub C25

ADJUSTMENT / SETTING